

CONTACTOR/OVERLOAD SUMMARY

HP	1 phs 115 V		1 phs 208 V		1 phs 230 V		3 phs 208 V		3 phs 230 V		3 phs 460 V		3 phs 575 V	
	Contactors	Overload	Contactors	Overload	Contactors	Overload	Contactors	Overload	Contactors	Overload	Contactors	Overload	Contactors	Overload
1/3	LC1K0910	LR2K0314	LC1K0910	LR2K0310	LC1K0910	LR2K0308	LC1K0910	LR2K0308	LC1K0910	LR2K0306	LC1K0910	LR2K0306	LC1K0910	LR2K0306
1/2	LC1K0910	LR2K0316	LC1K0910	LR2K0312	LC1K0910	LR2K0308	LC1K0910	LR2K0308	LC1K0910	LR2K0310	LC1K0910	LR2K0310	LC1K0910	LR2K0307
3/4	LC1K1210	LR2K0316	LC1K0910	LR2K0312	LC1K0910	LR2K0308	LC1K0910	LR2K0310	LC1K0910	LR2K0310	LC1K0910	LR2K0310	LC1K0910	LR2K0307
1	LC1K1210	LR2K0321	LC1K0910	LR2K0314	LC1K0910	LR2K0314	LC1K0910	LR2K0312	LC1K0910	LR2K0312	LC1K0910	LR2K0308	LC1K0910	LR2K0308
1 1/2	LC1D3210	LR2D1321	LC1K0910	LR2K0314	LC1K0910	LR2K0314	LC1K0910	LR2K0314	LC1K0910	LR2K0314	LC1K0910	LR2K0310	LC1K0910	LR2K0310
2	LC1D3210	LR2D1322	LC1K1210	LR2K0316	LC1K1210	LR2K0316	LC1K1210	LR2K0316	LC1K1210	LR2K0316	LC1K1210	LR2K0312	LC1K1210	LR2K0312
3			LC1D1810	LR2D1321	LC1K1210	LR2K0316	LC1K1210	LR2K0316	LC1K1210	LR2K0316	LC1K1210	LR2K0314	LC1K1210	LR2K0314
5			LC1D3210	LR2D2353	LC1D3210	LR2D2353	LC1D3210	LR2D1321	LC1K0910	LR2K0314	LC1K0910	LR2K0314	LC1K0910	LR2K0314
7 1/2					LC1D3210	LR2D2353	LC1D3210	LR2D1322	LC1K1210	LR2K0316	LC1K1210	LR2K0316	LC1K1210	LR2K0316
10					LC1D3210	LR2D2353	LC1D3210	LR2D2353	LC1D1810	LR2D1321	LC1D1810	LR2D1321	LC1K1210	LR2K0316
15					LC1D5011	LR2D3357	LC1D5011	LR2D3357	LC1D3210	LR2D1321	LC1D1810	LR2D1321	LC1D1810	LR2D1321
20					LC1D6511	LR2D3359	LC1D6511	LR2D3359	LC1D3210	LR2D2353	LC1D3210	LR2D2353	LC1D3210	LR2D1322